

**KBDID:** 150G

**Description:** Swiss German

**Status:** Registered

**National Layout:** Yes

**Regions:** Luxembourg, Switzerland

**Registration Date:** 1991-01-01

**Last Revision Date:** 1998-09-29

**Notes:**

1. Required for Switzerland & Luxembourg
2. The engraving of the physical keyboard for Switzerland may combine the logical layouts 150F and 150G by having a dual nomenclature on keys C10, C11 and D11. The keyboard driver supports either 150F or 150G at any given time, depending on user choice.
3. Euro added on 1998.09.29

## 150G - Switzerland



GLYPH	ROW	COL	LEVEL	IBM ID	DEAD KEY	NOT ENGRAVED	CHARACTER NAME	UNICODE ID
°	E	00	L2	SM19			Degree Symbol	U+00B0
§	E	00	L1	SM24			Section Symbol (USA)/Paragraph Symbol (Europe)	U+00A7
+	E	01	L2	SA01			Plus Sign	U+002B
1	E	01	L1	ND01			One	U+0031
	E	01	L3	SM13			Vertical Line/Logical OR	U+007C
"	E	02	L2	SP04			Quotation Marks	U+0022
2	E	02	L1	ND02			Two	U+0032
@	E	02	L3	SM05			At Sign	U+0040
*	E	03	L2	SM04			Asterisk	U+002A
3	E	03	L1	ND03			Three	U+0033
#	E	03	L3	SM01			Number Sign	U+0023
ç	E	04	L2	LC41			c Cedilla Small	U+00E7
4	E	04	L1	ND04			Four	U+0034
%	E	05	L2	SM02			Percent Sign	U+0025
5	E	05	L1	ND05			Five	U+0035
&	E	06	L2	SM03			Ampersand	U+0026
6	E	06	L1	ND06			Six	U+0036
¬	E	06	L3	SM66			Logical NOT/End Of Line Symbol	U+00AC
/	E	07	L2	SP12			Slash	U+002F
7	E	07	L1	ND07			Seven	U+0037

	E	07	L3	SM65			Vertical Line, Broken	U+00A6
(	E	08	L2	SP06			Left Parenthesis	U+0028
8	E	08	L1	ND08			Eight	U+0038
¢	E	08	L3	SC04			Cent Sign	U+00A2
)	E	09	L2	SP07			Right Parenthesis	U+0029
9	E	09	L1	ND09			Nine	U+0039
=	E	10	L2	SA04			Equal Sign	U+003D
0	E	10	L1	ND10			Zero	U+0030
?	E	11	L2	SP15			Question Mark	U+003F
'	E	11	L1	SP05			Apostrophe	U+0027
'	E	11	L3	SD11	Y		Acute Accent	U+00B4
`	E	12	L2	SD13	Y		Grave Accent	U+0060
^	E	12	L1	SD15	Y		Circumflex Accent	U+005E
~	E	12	L3	SD19	Y		Tilde Accent	U+007E
Q	D	01	L2	LQ02			Q Capital	U+0051
q	D	01	L1	LQ01			q Small	U+0071
W	D	02	L2	LW02			W Capital	U+0057
w	D	02	L1	LW01			w Small	U+0077
E	D	03	L2	LE02			E Capital	U+0045
e	D	03	L1	LE01			e Small	U+0065
€	D	03	L3	SC20			Euro symbol	U+20AC
R	D	04	L2	LR02			R Capital	U+0052
r	D	04	L1	LR01			r Small	U+0072
T	D	05	L2	LT02			T Capital	U+0054
t	D	05	L1	LT01			t Small	U+0074
Z	D	06	L2	LZ02			Z Capital	U+005A
z	D	06	L1	LZ01			z Small	U+007A
U	D	07	L2	LU02			U Capital	U+0055
u	D	07	L1	LU01			u Small	U+0075
I	D	08	L2	LI02			I Capital	U+0049
i	D	08	L1	LI01			i Small	U+0069
O	D	09	L2	LO02			O Capital	U+004F
o	D	09	L1	LO01			o Small	U+006F
P	D	10	L2	LP02			P Capital	U+0050
p	D	10	L1	LP01			p Small	U+0070
è	D	11	L2	LE13			e Grave Small	U+00E8
ü	D	11	L1	LU17			u Diaeresis Small	U+00FC
[	D	11	L3	SM06			Left Bracket	U+005B
!	D	12	L2	SP02			Exclamation Point	U+0021
¨	D	12	L1	SD17	Y		Diaeresis/Umlaut Accent	U+00A8
]	D	12	L3	SM08			Right Bracket	U+005D
A	C	01	L2	LA02			A Capital	U+0041
a	C	01	L1	LA01			a Small	U+0061
S	C	02	L2	LS02			S Capital	U+0053
s	C	02	L1	LS01			s Small	U+0073
D	C	03	L2	LD02			D Capital	U+0044
d	C	03	L1	LD01			d Small	U+0064
F	C	04	L2	LF02			F Capital	U+0046

f	C	04	L1	LF01			f Small	U+0066
<b>G</b>	C	05	L2	LG02			G Capital	U+0047
g	C	05	L1	LG01			g Small	U+0067
<b>H</b>	C	06	L2	LH02			H Capital	U+0048
h	C	06	L1	LH01			h Small	U+0068
<b>J</b>	C	07	L2	LJ02			J Capital	U+004A
j	C	07	L1	LJ01			j Small	U+006A
<b>K</b>	C	08	L2	LK02			K Capital	U+004B
k	C	08	L1	LK01			k Small	U+006B
<b>L</b>	C	09	L2	LL02			L Capital	U+004C
l	C	09	L1	LL01			l Small	U+006C
é	C	10	L2	LE11			e Acute Small	U+00E9
ö	C	10	L1	LO17			o Diaeresis Small	U+00F6
à	C	11	L2	LA13			a Grave Small	U+00E0
ä	C	11	L1	LA17			a Diaeresis Small	U+00E4
{	C	11	L3	SM11			Left Brace	U+007B
£	C	12	L2	SC02			Pound Sterling Sign	U+00A3
\$	C	12	L1	SC03			Dollar Sign	U+0024
}	C	12	L3	SM14			Right Brace	U+007D
>	B	00	L2	SA05			Greater Than Sign/Less Than Sign (Arabic)	U+003E
<	B	00	L1	SA03			Less Than Sign/Greater Than Sign (Arabic)	U+003C
\	B	00	L3	SM07			Backslash	U+005C
<b>Y</b>	B	01	L2	LY02			Y Capital	U+0059
y	B	01	L1	LY01			y Small	U+0079
<b>X</b>	B	02	L2	LX02			X Capital	U+0058
x	B	02	L1	LX01			x Small	U+0078
<b>C</b>	B	03	L2	LC02			C Capital	U+0043
c	B	03	L1	LC01			c Small	U+0063
<b>V</b>	B	04	L2	LV02			V Capital	U+0056
v	B	04	L1	LV01			v Small	U+0076
<b>B</b>	B	05	L2	LB02			B Capital	U+0042
b	B	05	L1	LB01			b Small	U+0062
<b>N</b>	B	06	L2	LN02			N Capital	U+004E
n	B	06	L1	LN01			n Small	U+006E
<b>M</b>	B	07	L2	LM02			M Capital	U+004D
m	B	07	L1	LM01			m Small	U+006D
;	B	08	L2	SP14			Semicolon	U+003B
,	B	08	L1	SP08			Comma	U+002C
:	B	09	L2	SP13			Colon	U+003A
.	B	09	L1	SP11			Period/Full Stop	U+002E
—	B	10	L2	SP09			Underline/Continuous Underscore	U+005F
-	B	10	L1	SP10			Hyphen/Minus Sign	U+002D

**Notes:**

The engraving of physical keyboard for Switzerland may combine the logical layouts 150-F and 150-G by having a dual nomenclature on keys C10, C11 and D11. The keyboard driver supports either 150-F or 150-G at any given time, depending on user choice.